

V I D E O

4 X 4 Video Matrix Switcher

Sequence 1 to 4 Inputs through 1 to 4 Outputs

V
S
4
X
4



The NetMedia VS4X4 Matrix Switcher allows any combination of 1 to 4 baseband video sources to be independently sequenced through any of 1 to 4 possible outputs. Great for surveillance and monitoring in commercial, residential, and specialty applications. Combine one or more sequenced outputs with a NetMedia Digital Channel Modulator to create your own TV channel and view the signal on multiple TVs.

Features:

- Supports NTSC or PAL format in Color or B/W
- Selectable for 1 to 4 Inputs and 1 to 4 Outputs
- Precision digital sequencing, user selectable
- Manual or automatic switching
- Microprocessor controlled
- Memory retained during power outages
- Ideal for battery powered applications
- Rugged aluminum enclosure
- Includes Wall Transformer
- 1 Year Limited Warranty



Specifications

Switching Time User Selectable:	1 - 255 Seconds
Video Frequency Response	
Total Bandwidth:	12 Mhz.
Video Crosstalk:	-70 db
Video Inputs:	4 - RCA, 75 Ohm BNC Adaptor Optional
Video Outputs:	4 - RCA, 75 Ohm BNC Adaptor Optional
Sequence Position Indicators:	2 Status LEDs 4 Input LEDs 4 Output LEDs
Power Requirement:	12V DC 300mA CL2, UL Approved Indoor Use Only
Size:	3.5" x 5.5" x 0.9"
Weight:	8.5 oz.

S
W
I
T
C
H
E
R
S

10940 North Stallard Place, Tucson, Arizona 85737
(520) 544-4567 Fax: (520) 544-0800
www.netmedia.com