

V
I
D
E
O

Single Channel MicroModulator™

Digitally Controlled Audio & Video
For Making Your Own TV Channels

M
M
7
0



The NetMedia MM70 single channel MicroModulator is great for security surveillance, audio/video distribution and video monitoring. View a camera, VCR, laserdisc, DVD or satellite receiver on a TV channel you choose and distribute it to every TV in the home. Combine with existing TV channels for seamless CCTV systems.

Features:

- World's First 100% Digital Modulator
PLL Locked Audio & Video
Zero parts to drift
- Combines with existing TV channels
- UHF & Cable coverage
- Internally generated test pattern
- Memory retained during power outages
- Rugged aluminum enclosure
- Includes Wall Transformer
- 5 Year Limited Warranty

Specifications

Output Frequency Range:	Ch. 14-69 UHF Ch. 70-94 CATV Ch. 100-125 CATV
Modulation Method:	Digital Audio, Video Crystal Stabilized PLL
Output Level:	Selectable, 0 to +30dBmV
Video Output Connector:	F-connector, 75 Ohm
Video Input Connector:	RCA, 75 Ohm, 1 Vp-p
Audio Input Connector:	3.5mm Stereo Jack 75,000 Ohm, 1 Vp-p
Power Requirement:	12V DC, 100mA CL2, UL Approved Indoor Use Only
Size:	3.2" x 2.2" x 0.9"
Weight:	4.0 oz

M
O
D
U
L
A
T
O
R
S



10940 North Stallard Place, Tucson, Arizona 85737
(520) 544-4567 Fax: (520) 544-0800
www.netmedia.com